

# marantz



AMP 30

## 6-Channel Power Amplifier

Reference 6-channel, 200-watt-per-channel slimline amplifier featuring Marantz HDAM, Current Feedback Amplification, and balanced line level inputs. Pair with AV 30 to create an exceptional home theater. Combine with additional AMP 30, AMP 20, or AMP 10 power amplifiers to drive more complex speaker configurations.

- **Detailed and immersive sound transforms your home theater**
- **200 watts per channel into 8Ω / 400 watts per channel into 4Ω**
- **Six slimline channels power dedicated home theaters**
- **Bi-amp mode drives high- and low-frequency sections of loudspeakers independently**
- **BTL Mode: Three channels of 400W**
- **Balanced XLR input is ideal for reducing input noise**
- **Porthole with analog meter measures output**
- **Soft side lights cast a warm glow on the amplifier front panel**
- **Elegant slimline design matches rich, warm sound**



The Most Musical Sound

# AMP 30

## Technical Specifications

| Inputs/Outputs                               |                             |  |
|--|-----------------------------|--|
| Audio  | Main Amplifier In           | Balanced & Unbalanced: 6ch (Exclusive use by a selector switch)                |
| Other  | Speaker Terminal            | SPKT-1+  |
|  | Number of Speaker Terminals | 6  |
|  | Bi-Amp Drive / BTL Drive    | Yes / Yes  |
|  | Level Meter                 | Yes  |
| Multi-Room                                   |                             |  |
| RS232 Control                                |                             | Yes  |
| IR Flasher In                                |                             | Yes  |
| Marantz Remote Bus                           |                             | Yes  |
| DC Trigger Input / Output                    |                             | 1 / 1  |
| Specifications                               |                             |  |
| Number of Power Amps                         |                             | 6  |
| Power Output (8 ohm, 1 kHz, 0.05% 2ch Drive) | Normal / BTL                | 200W / 400W  |
| Power Output (4 ohm, 1 kHz, 0.7% 2ch Drive)  | Normal                      | 400W   |
| Power Output (8 ohm, 1 kHz, 0.7% 5ch Drive)  | Normal                      | 200W   |
| General                                      |                             |  |
| Front Display                                |                             | Level Meter  |
| Auto Power Off                               |                             | Yes  |
| Metal Front Panel                            |                             | Yes  |
| Power Consumption                            |                             | 300W   |
| Power Consumption, No-Sound (ECO On / Off)   |                             | 70W  |
| Standby Consumption                          |                             | 0.2W   |
| Maximum Dimensions (W x D x H)               |                             | 442 x 442 x 111 mm   |
| Weight                                       |                             | 10.0 kg  |
| What's in the Box                            |                             | Main unit, quick start guide, AC cord, Amp control cable, Remote control cable |
| EAN  |                             | 0747192145705  |



Design and specifications are subject to change by Marantz without notice.

[www.marantz.com](http://www.marantz.com)

